NAVAL POSTGRADUATE SCHOOL MONTEREY CA F/G 12/1 A GRAPHICAL TEST BED FOR ANALYZING AND REPORTING THE RESULTS OF--ETC(U) MAR 82 D G LINNEBUR AD-A118 214 UNCLASSIFIED NL 1 or 2

NAVAL POSTGRADUATE SCHOOL



Monterey, California



THESIS

A GRAPHICAL TEST BED FOR ANALYZING AND REPORTING THE RESULTS OF A SIMULATION EXPERIMENT

by

David George Linnebur

March 1982

Thesis Advisor:

P. A. W. Lewis

Approved for public release; distribution unlimited

82 08 16 170

SECURITY CLASSIFICATION OF THIS PAGE (Then Date Enter

	REPORT DOCUMENTATION PAGE	READ INSTRUCTIONS BEFORE COMPLETING FORM
1.	AD ALL & 214	1. RECIPIENT'S CATALOG NUMBER
1	TITLE (and Subitio)	S. TYPE OF REPORT & PERIOD COVERED
	A Graphical Test Bed for Analyzing and	Master's Thesis March 1982
	Reporting the Results of a Simulation Experiment	4. PERFORMING ORG. REPORT NUMBER
7.	AUTHOR(e)	4. CONTRACT OR GRANT NUMBER(s)
	David George Linnebur	
10.	PERFORMING ORGANIZATION NAME AND ADDRESS	10. PROGRAM ÉLÉMENT, PROJECT, TASK AREA à WORK UNIT NUMBERS
	Naval Postgraduate School Monterey, California 93940	
111	CONTROLLING OFFICE NAME AND ADDRESS	12. REPORT DATE
l	Naval Postgraduate School	March 1982
İ	Monterey, California 93940	112
14.	MONITORING AGENCY NAME & ADDRESS(II different from Controlling Office)	15. SECURITY CLASS, (of this report)
İ		Unclassified
		ISA. OECLASSIFICATION/DOWNGRADING SCHEDULE
16.	DISTRIBUTION STATEMENT (of this Report)	
	Approved for public release; distribution	n dhiimited
17.	DISTRIBUTION STATEMENT (of the obstract antered in Block 26, if different fre	an Report)
18.	SUPPLEMENTARY NOTES	
19.	KEY WORDS (Continue on reverse side il necessary and identify by block number)	· · · · · · · · · · · · · · · · · · ·
	Simulation, graphics, box plots, regress bias reduction	ion, output analysis,
20.	ABSTRACT (Continue on reverse side if necessary and identify by block manber)	
	A graphical test bed in which the result ment can be reported and analyzed is desis based on the regression adjusted graph (RAGE) methodology developed by Heidelber for regenerative simulations. From the ciated numerics the experimenter can summer	cribed. The test bed hics and estimation rger and Lewis [Ref.1] graphics and the asso-

BEUMTY ELASHFIEATION OF THIS PAGE/When Rose Sa

simultaneously relative properties, such as bias, normality and standard deviation, of several estimators of a characteristic of a population for up to eight sample sizes. The graphics is supported on a line printer to make it and the program portable.

	Access to Mar
	40
	Lise Lisenspeed <u>(j</u> Judification <u> </u>
DIE	Principal Distribution/
COPY	Availabil ky Avans Avail orajisa Didt De oinl
	A

DD Form, 1473 S/N 0102-014-6601

Unclassified

SECURITY ELAMPICATION OF THIS PAGETMEN Bete Entered!

Approved for public release; distribution unlimited

A Graphical Test Bed

For Analyzing and Reporting

The Results of a

Simulation Experiment

by

David George Linnebur Captain, United States Marine Corps B.A., Saint Mary of the Plains College, 1975

Submitted in partial fulfillment of the requirements for the degree of

MASTER OF SCIENCE IN OPERATIONS RESEARCH

from the

NAVAL POSTGRADUATE SCHOOL March 1982

Approved by:

P.Q.W. Function

Thesis Advisor

Second Reader

Chairman, Repartment of Operations Research

Dean of Information and Policy Sciences

ABSTRACT

A graphical test bed in which the results of a simulation experiment can be reported and analyzed is described. The test bed is based on the regression adjusted graphics and estimation (RAGE) methodology developed by Heidelberger and Lewis (Ref. 1) for regenerative simulations. From the graphics and the associated numerics the experimenter can summarize and see simultaneously relative properties, such as bias, normality and standard deviation, of several estimators of a characteristic of a population for up to eight sample sizes. The graphics is supported on a line printer to make it and the program portable.

TABLE OF CONTENTS

I.	INTRODUCTION 1	.1
II.	USAGE 1	4
III.	DESCRIPTION OF RAGE ARGUMENTS 2	4
	A. DATA ARRAYX 2	4
	B. SAMPLE SIZEN 2	4
	C. NUMBER OF REPLICATIONSM 2	5
	D. SUBSAMPLE SIZE ARRAYNE 2	5
	E. NUMBER OF SUBSAMPLE SIZES (Box Plots)L 2	6
	F. DEGREE OF REGRESSIOND 2	.7
	G. REDUCED GRAPHICSRG 2	7
	H. SCALING ESTIMATORS INDIVIDUALLYSEI 2	8
	I. SETTING THE VERTICAL SCALESVS 2	8
	J. MINIMUM VALUE OF THE VERTICAL SCALEYMIN 2	9
	K. MAXIMUM VALUE OF THE VERTICAL SCALEYMAX 2	9
	L. NUMBER OF ESTIMATORSNEST 2	9
	M. ESTIMATOR FUNCTIONSEST1, EST2, EST3 3	30
	N. DESCRIPTION OF ESTIMATORSTTL1, TTL2, TTL3 - 3	0
IV.	EXAMPLE OF A PROGRAM USING RAGE 3	3 2
v.	A COMPARATIVE STUDY OF ESTIMATORS FOR THE GAMMA SHAPE PARAMETER	3 5
	A. EXAMING THE GAMMA DISTRIBUTION FOR THE SHAPE PARAMETER (K=5.0) 3	8 8
	1. Case 1, Example 1: Small Subsample Sizes	ξQ

		2.	Case 1, Example 2: Small Subsample Sizes and Large Replications (K=5.0)	47
		3.	Case 1, Example 3: Large Subsample Sizes and Large Replications (K=5.0)	61
	В.		MING THE GAMMA DISTRIBUTION FOR THE SHAPE AMETER (K=0.2)	70
		1.	Case 2, Example 1: Small Subsample Sizes and Small Replications (K=0.2)	70
		2.	Case 2, Example 2: Small Subsample Sizes and Large Replications (K=0.2)	77
		3.	Case 2, Example 3: Large Subsample Sizes and Large Replications (K=0.2)	86
RAGE	PRO	GRAM	LISTING	93
LIST	OF	REFER	ENCES	110
ואדדו	ΓΔΙ	חוכת	TRUTTON LIST	111

LIST OF TABLES

1.	Standard deviations of estimates of the shape parameter using the moment and MLE estimators for small sample sizes (replications=2) 39
2.	Skewness coefficients of the estimates of the shape parameter using the moment and jacknifed moment estimators (replications=2)
3.	Skewness coefficients of the estimates of the shape parameter using the MLE and jacknifed MLE estimators (replications=2)
4.	Standard deviations of the estimates of the shape parameter using the moment and MLE estimators for varying sample sizes (replications=100)
5.	Bias coefficients for each estimator's population of estimates and their standard deviations for small and large replications (M=2 and M=100) 52
6.	Standard deviations of the population of estimates of the shape parameter for each estimator for subsample sizes 500 and 2000
7.	Bias and variance comparisons for varying subsample sizes and shape parameters 88

LIST OF FIGURES

1.	M replications, each of sample size N 15	5
2.	Subsectioning MxN samples into subsamples of size n_k , $k=1$,, K	ó
3.	(a, b, c, d) Full scale graphics of 4 estimators (Moment, MLE, Jacknifed Moment and Jacknifed MLE) estimating the shape parameter (K=5.0) of the gamma distribution with small subsamples (33-500) and small replications (2)	3
4.	(a, b, c, d) Full scale graphics of 4 estimators (Moment, MLE, Jacknifed Moment and Jacknifed MLE) estimating the shape parameter (K=5.0) of the gamma distribution with small subsamples (33-500) and large replications (100)	3
5.	(a, b, c, d) Reduced graphics of 4 estimators (Moment, MLE, Jacknifed Moment and Jacknifed MLE) estimating the shape parameter (K=5.0) of the gamma distribution with small subsamples (33-500) and large replications (100)	7
6.	(a, b, c, d) Full scale graphics of 4 estimators (Moment, MLE, Jacknifed Moment and Jacknifed MLE) estimating the shape parameter (K=5.0) of the gamma distribution with large subsamples (100-2000) and large replications (25)	4
7.	(a, b) Reduced graphics of 2 estimators (Moment and MLE) estimating the shape parameter (K=5.0) of the gamma distribution with large subsamples (100-2000) and large replications (100)	8
8.	(a, b, c, d) Full scale graphics of 4 estimators (Moment, MLE, Jacknifed Moment and Jacknifed MLE) estimating the shape parameter (K=0.2) of the gamma distribution with small subsamples (33-500) and small replications (2)	3
9.	(a, b, c, d) Full scale graphics of 4 estimators (Moment, MLE, Jacknifed Moment and Jacknifed MLE) estimating the shape parameter (K=5.0) of the gamma distribution with small subsamples (33-500) and large replications (100)	0

10.	(a, b) Reduced graphics of 2 estimators (Moment and MLE) estimating the shape parameter (K=0.2) of the gamma distribution with small subsamples (33-500) and large replications (100)	84
11.	(a, b, c, d) Full scale graphics of 4 estimators (Moment, MLE, Jacknifed Moment and Jacknifed MLE) estimating the shape parameter (K=0.2) of the gamma distribution with large subsamples (100-2000) and large replications (25)	89

ACKNOWLEDGEMENT

I wish to acknowledge two people that contributed to my thesis research. First is Professor P. A. W. Lewis who was my thesis advisor. His time was always available and his advice and support contributed a great deal to my knowledge and the completion of this thesis for which I am grateful.

Second I would like to thank Professor Luis C. Uribe who was the primary contributor of the graphics provided by the "RAGE" FORTRAN program which is a part of this thesis. Those changes and additions that were made were frequently with his advice and assistance and contributed significantly to the final program.

I. INTRODUCTION

During the course of a simulation experiment the experimenter is frequently confronted with the problem of estimating some function or parameter from the generated data. He will usually have a choice of one or more estimators, parametric or nonparametric, that can be used to estimate the function or parameter. These estimators will vary in their statistical properties. Some will estimate with low variance but contain bias, others will have just the opposite characteristics and still others will contain varying degrees of both. How these different estimators compare in relation to each other as well as over varying sample sizes are of concern to the experimenter. Comparison of estimators are important in that they help the experimenter to choose the most appropriate estimator for his particular analysis. Comparisons may also be helpful in deciding whether a new estimator is of any use. The appropriate estimator to use is a function of the bias, variance and nonnormality in the estimate for available run length (sample size).

When the simulated data from which the properties of the estimators is to be examined is independent and identically distributed (iid) it can be sectioned into M independent blocks of specified sample size (N). From each of these blocks the estimator can be applied to all subsamples of

size n_k , thereby creating samples of estimates of varying size for each estimator. As a first cut at the properties of the estimators, box plots of these samples of estimates are drawn for subsample sizes n_k (see, e.g. Figure 3a).

However, something is usually known about the properties of the estimators and these properties can be used to enhance the graph of box plots versus subsample size, n_k . Thus it is often known that bias in the estimator is a polynomial in 1/n, and the variance of the estimator is a polynomial in $\frac{1}{n}$, $\frac{1}{n^{1.5}}$, $\frac{1}{n^2}$, ... Also the estimators are usually asymptotically normally distributed. Consequently the graphs are enhanced by an estimated unbiased regression line for the mean of the estimates of the parameter as well as a horizontal line for the regression-estimated expected value of the parameter (asymptote). A regression is also performed for the variance structure of the estimators and the sample characteristics (kurtosis and skewness) are given under each box plot to assist in judging the convergence to normality.

Heidelberger and Lewis [Ref. 1] used this methodology in the context of regenerative simulation to develop a procedure and protocol to produce unbiased and normally distributed regression adjusted regenerative estimates (RAGE), with a given precision or for total available computing time. However, the graphics associated with this procedure required a Tektronic 4013 terminal using an APL graphics package making

its use limited to those organizations possessing such a terminal. The protocol also requires a relatively experienced user to properly interpret the graphical and statistical output and to apply the sequential steps of the protocol.

The purpose of this thesis is to apply the methodology developed by Heidelberger and Lewis [Ref. 1] to comparing the bias and variance of estimators of a parameter from simulated output. This objective also includes supporting the graphics associated with the methodology on a line printer to make its use more accessible.

Details of the graphics and methodology are given in Chapter II, entitled USAGE. Details of the arguments of the RAGE program are given in Chapter III and a sample program using the RAGE graphics is given in Chapter IV. All the user has to supply is the input data and FORTRAN functions to compute the estimators for any given subset of data.

A comparative study of estimators of the gamma shape parameter using the graphical test bed RAGE is given in Chapter V. This comparative study illustrates the different properties of estimators that can be seen with regression adjusted graphics as sample size increases.

II. USAGE

The regression adjusted graphics and estimating (RAGE) program is designed to evaluate distributional properties of one or more estimators as a function of sample size from a stationary series of raw data. These estimators are programmed as functions by the user and declared external in the main program. The graphical and numerical results that accompany each estimator are varied and will depend to some extent on the options desired by the user. The purpose of the following discussion is to explain the graphical and numerical output as well as how they were obtained and some of the options available to the user.

The general procedure begins with a given iid data base or one that has been simulated and an unknown parameter or population characteristic, Θ , that is to be estimated by an estimator, $\widehat{\Theta}$, from the data. The experimenter must first decide on the number of independent blocks or sections (M) of size N the data is to be sectioned into. These M sections or blocks will henceforth be referred to as replications; the terminology will seem more appropriate as the discussion continues. The number of replications (M) can alternatively be determined indirectly by the sample size (N) desired in each section. In either case MxN must not exceed the total allowable sample size. This sectioning of the data into

M replications of sample size N is represented in Figure 1 where the entire block represents the MxN samples from the total sample population.

N	^m 1
N	m ₂
•	. m _i i=1,, M
N	m _M

Figure 1: M replications, each of sample size N Within each replication the experimenter must decide on the subsample sizes that the estimator, $\hat{\Theta}$, is to use in estimating the parameter. The number of different subsample sizes, K, that can be used to resection the same data can vary from one to eight and the size of each subsample can vary from one to the size of the sample, N. This repeated subsectioning of the same data is represented pictorially by Figure 2 where [x] refers to the highest integer less than or equal to x and r_k , $k=1, \ldots$, K refers to the number of estimates possible from a sample of size N using subsample sizes n_k , $k=1, \ldots$, K to estimate the parameter. Each box or rectangle in Figure 2 represents the same MxN data set with the same M replications of size N subsectioned into different sections of size n_k . Note that the n_k 's divide N evenly in Figure 2. This is not necessary but certainly desirable since all available information will be utilized.

Sample size		To	tal	Samp	les	MxN	Section (Rep.)	Population of Estimates for subsample size n	
N	n ₁	n ₁	n ₁	n ₁	n ₁	n ₁	n ₁	m ₁	
N	n ₁	n ₁	n ₁	n ₁	n ₁	n ₁	n ₁	m ₂	
•		:	:	:	•	·	·]:	$\begin{bmatrix} N \\ n_1 \end{bmatrix} \times M = r_1 M$
•	·	•	•	•	•	•	•	<u> </u>	l ⁿ 1
N	n ₁	n ₁	n ₁	n ₁	n ₁	n ₁	n ₁	m _M	
					,			_	
N	n ₂	n	2	n ₂	n ₂	n ₂		m ₁	
N	n ₂		2	n ₂ r		n ₂ n ₂	m ₂		
•	·	•		•	•	•		1 .	
•	1:		}	:	•	1:		1:	$ \frac{N}{n_2} \times M = r_2 M $
N	n ₂	n	2	n ₂	n ₂	n ₂		m _M	[]
	<u> </u>			ــــــاـ		<u> </u>			
•				•				•	•
•				•			•	•	
N		nk	.	nk	n _k			m ₁	
N	ļ		n_k n_k		nk			m ₂	
•	•		1			•		1.	Γ,,]
•				•		•			$\frac{N}{n_k} \times M = r_k M$
N	nk			nk		nk		m _M	
								-	

Figure 2: Subsectioning MxN samples into subsamples of size n_k , k=1, ..., K

If each subsample size $(n_k, k=1, \ldots, K)$ produces a total of r_k , $k=1, \ldots$, K estimates per sample of size N then there will be a population of estimates from the M replications that total Mxr_k , $k=1, \ldots$, K for each subsample. For each

population of estimates from each subsample $(n_k, k=1, \ldots, K)$ box plots are plotted so that the distribution of the estimates for the varying subsample sizes can be seen graphically.

In addition to these box plots of the estimates, a regression adjusted estimate (RARE) of the parameter is computed and plotted over the boxplots. In addition to the RARE estimate, unbiased RARE estimates out to a specified number of terms determined by the user are computed and plotted on the graph (The mathematical derivation of the RARE and unbiased RARE estimates are given later in this section). The unbiased RARE estimates are computed as a function of subsample size and plotted in conjunction with the RARE estimate so that a comparison of the two values can be made graphically and the evolution to an unbiased state can be seen as the subsample size increases.

This idea can be made clearer through the use of an example and its associated graphics and numerics, Figure 4a. Here an independent and identically distributed sample of 50,000 gamma distributed random numbers (shape parameter, K=5.0) has been generated and sectioned into M=100 sections (replications) with each replication containing N=500 random numbers (sample size). This information is printed at the top of the graph for future identification. The experimenter chose eight different subsample sizes at which to examine the parameter (33, 50, 71, 125, 166, 250 and 500). These subsample sizes $(n_k's)$ are printed on the horizontal scale

of the graph. The population of estimates of the parameter at each subsample size are then plotted as vertical box plots above these numbers. When the population of estimates determined from a subsample size is less than nine, box plots are omitted and the values of these estimates are simply plotted with the sumbol "O" on the graph. There are no estimates with populations totaling less than nine in Figure 4a but the graphical output for such cases can be seen in Figure 3a where subsample sizes, 125, 166, 250 and 500 total less than nine estimates.

The horizontal scale of the graph is scaled roughly to the minimum and maximum subsample sizes with the box plot of each subsample's estimates spaced proportionally. However, when subsample size differences are relatively small so that overlap of the box plots would occur, a minimum of six spaces between centers of box plots is left to prevent the graphics from becoming confused.

The vertical scale of the graph is determined by the minimum and maximum values from the population of estimates determined from the smallest subsample size (n_1) . It is assumed here that subsequent subsample sizes (n_2, n_3, \ldots) will be large in relation to the smallest subsample size (n_1) so that estimates produced from these will be within the range of that determined from the smallest subsample size. This assumption appears tenable if the range of estimates is compared in Figure 4a for increasing subsample sizes.

The vertical scale of Figure 4a is not scaled to the minimum and maximum value of the estimates determined from the smallest subsample size $(n_1=33)$. This is because the RAGE program can evaluate up to three different estimators at one time and two alternate estimators (Figures 4b & 4c) were also used to estimate the parameter. An option was entered to scale all three estimators to the same scale and it chose the minimum and maximum values from all the estimates produced by all three estimators using the smallest subsample size $(n_1=33)$. By comparing Figures 4a, 4b and 4c it can be seen that the maximum value was taken from the first estimator, Figure 4a, and the minimum value was taken from the third estimator, Figure 4c. Other scaling options will be discussed in detail in the following chapter.

Below the graph statistical results as they pertain to the population of estimates for each subsample size are printed. These statistics include the sample mean, standard deviation, standard deviation of the mean, skewness and kurtosis. Thus, for example, in Figure 4a at subsample size n_1 =33 there is a population of $[N/n_1]xM = r_1xM = [500/33]x100 = 150$ estimates for which a sample mean, standard deviation, standard deviation of the mean, skewness and kurtosis is computed. The subsample sizes these statistics refer to are labeled across the top.

As mentioned earlier, in addition to box plots and associated statistics of the estimates, RARE and unbiased RARE

estimates of the parameter are computed and plotted on the graph. The degree of regression, D, for the computations of the unbiased RARE estimates is determined by the user and printed at the top of the graph for future reference. The RARE estimate is the regression coefficient β_0 and is the estimated asymptotic expected value of the parameter being estimated. The unbiased RARE estimates are determined by the regression coefficients, β_1 , β_2 , ..., β_d , the subsample size, n, and the RARE estimate, β_0 , using the following formula:

$$\beta_0 + \beta_1 \frac{1}{n} + \beta_2 \frac{1}{n^2} + \dots + \beta_d \frac{1}{n^d}$$

A set of regression coefficients $(\beta_0, \beta_1, \ldots, \beta_d)$ is determined from the mean of the population of estimates (dependent variable) at each subsample size for each replication. The M regressions that determine the M sets of coefficients $(\beta_0, \beta_1, \ldots, \beta_d)$ are represented by the following formula:

$$\mathbf{\hat{G}}(n_1) = \beta_0 + \beta_1 \frac{1}{n_1} + \beta_2 \frac{1}{n_1^2} + \dots + \beta_d \frac{1}{n_d^d}$$

$$\vdots \qquad \vdots \qquad \vdots \qquad \vdots \qquad \vdots \qquad \vdots \qquad \vdots$$

$$\mathbf{\hat{g}}(n_k) = \beta_0 + \beta_1 \frac{1}{n_k} + \beta_2 \frac{1}{n_k^2} + \dots + \beta_d \frac{1}{n_k^d}$$

 $m = 1, \ldots, M$

where
$$\hat{\Theta}(n_k) = \sum_{i=1}^{r_k} \hat{\Theta}_{i}(n_k)$$
 $k = 1, ..., K$ $m = 1, ..., M$

The regression coefficients, to determine the RARE and unbiased RARE estimates, are the average values determined from these M regressions applied to the M replications. The mean, variance and standard deviation of these coefficients are printed below the graph below the subsample size statistics.

As mentioned earlier, the first coefficient, β_0 , is the estimated asymptotic expected value of the parameter being estimated (RARE). Its mean from the M regressions is printed as a horizontal dashed line across the graph. As the subsample size increases the bias in the unbiased RARE estimates becomes smaller and the unbiased RARE estimates (dotted line) will asymptotically approach the RARE estimate (dashed line). In Figure 4a the estimated expected value or asymptote $\beta_0 = 4.98$ and the bias coefficients for the three degree (D) regression are: $\beta_1 = 16.50$, $\beta_2 = -182.21$, $\beta_3 = 3659.04$.

The variance regression coefficients are determined from the variances of the population of estimates for each subsample size (dependent variable) and evaluating the single regression

$$VAR(\hat{\Theta}(n_1)) = \alpha_1 \frac{1}{n_1} + \alpha_2 \frac{1}{n_1^{1.5}} + \dots + \alpha_{d+1} \frac{1}{n_1^{(d+2)/2}}$$

$$\vdots \qquad \vdots \qquad \vdots \qquad \vdots$$

$$VAR(\hat{\Theta}(n_k)) = \alpha_1 \frac{1}{n_k} + \alpha_2 \frac{1}{n_k^{1.5}} + \dots + \alpha_{d+1} \frac{1}{n_k^{(d+2)/2}}$$

where
$$VAR(\widehat{\Theta}(n_k)) = \frac{\sum_{m=1}^{M} \sum_{i=1}^{r_k} \left[\widehat{\Theta}(n_k) - m\widehat{\Theta}_i(n_k)\right]^2}{r_k^{M-1}}$$

$$k=1, \ldots, K$$

and
$$\widehat{\mathfrak{G}}(n_k) = \frac{\sum_{m=1}^{M} \sum_{i=1}^{r_k} \widehat{\mathfrak{G}}_i(n_k)}{r_k^M}$$
 $k=1,\ldots,K$

The four (D+1) variance regression coefficients for Figure 4a are; α_1 = 58.37, α_2 = 174.72, α_3 = -1500.13, and α_4 = 5446.25. The variance regression coefficients derived here can be used to obtain an approximate variance for a specified subsample size by substituting the subsample size for n_k in any one of the above regression equations along with the variance coefficients $(\alpha_1, \alpha_2, \ldots)$ and completing the computation.

Below the variance regression coefficients the minimum and maximum value of the vertical scale is printed. The purpose of this information is to allow the user to scale other estimators of the same parameter to the same scale. It can be used when the number of estimators exceeds three

(the maximum number of estimators RAGE can use in a single run) or when subsequent runs for different conditions are desired to be of the same scale for graphical comparisons.

A final identifying feature of the graphics is a section at the very bottom of the graphical output which allows the user to identify the estimator that was used in estimating the parameter. In Figure 4a this estimator was the moment estimator, i.e. the reciprocal of the estimated coefficient of variation squared.

III. DESCRIPTION OF RAGE ARGUMENTS

The RAGE program has the calling sequence: call RAGE(X,N,M,NE,L,D,RG,SEI,SVS,YMIN,YMAX,NEST,EST1,TTL1,EST2, TTL2,EST3,TTL3). The arguments are relatively easy to understand but in several cases are related and must meet certain restrictions. For this reason a detailed description of each argument is given, as well as any restrictions or limitations that must be met within or between arguments. Following this detailed discussion an example is given in Chapter IV on how to set up the main program and the estimator functions.

A. DATA ARRAY...X

The X argument is a single precision Real*4 array containing the data from which the parameter is to be estimated. The only restriction is that the size of the X array must not exceed 50,000 which is the maximum sample size that RAGE can store.

B. SAMPLE SIZE...N

The number of data elements per section or sample size is designated by the integer N. Depending on the minimum sample size required by the estimator, N can vary from 1 to 50,000. The sample size, N, times the number of sections, M, cannot exceed 50,000 (the maximum number of data elements

stored in the array X). If M times N exceeds 50,000 an error message will be printed and execution will terminate. If M times N exceeds the number of data elements stored by the user in the array X then no error message will be printed and the program will execute giving unpredictable results or an abnormal ending will occur.

C. NUMBER OF REPLICATIONS...M

The number of sections or replications the array X is sectioned into is determined by the integer value assigned to M. The number assigned to M is also the number of regressions that will be run to determine the regression coefficients β_0 , β_1 , $...\beta_d$. The number of regressions is limited to one hundred and therefore M is limited to a maximum value of one hundred. An error message will be printed and execution will terminate if M is greater than one hundred or less than one. If M is equal to one the variance and standard deviation of the regression coefficients for the unbiased estimate will not be printed since they will not exist.

D. SUBSAMPLE SIZE ARRAY...NE

The argument NE is an integer array of size eight containing the subsample sizes $(n_k, k=1, \ldots, K)$ the estimator is to use in estimating the parameter. The values in the array NE should be ordered from smallest to largest or a warning message will be issued to indicate the vertical scale of the graph may not be large enough to include all

estimates. RAGE will use the population of estimates determined from the subsample size stored in NE(1) to determine the vertical scale of the graph. If NE(1) is not the smallest value the range of the graphics may not be large enough to include outliers determined from subsequent smaller subsample sizes.

Due to storage limitations a maximum of 12,500 estimates is permissable. Since NE(1) will produce the most estimates, the user can determine the total number of estimates using the formula Mx[N/NE(1)]. If this value exceeds 12,500 an error message will result stating this limitation has been exceeded and execution will terminate. Corrective action can be taken by increasing NE(1) or decreasing M or N.

E. NUMBER OF SUBSAMPLE SIZES (BOX PLOTS)...L

The user can select the number of subsample sizes to be used from the array NE(8) by assigning an integer value to the argument L. The argument, L, can take on values between one and eight. RAGE will then select the first L subsample sizes from NE(8), compute the population of estimates of the parameter with each, graph the box plots and print the associated statistics. If L is not an integer value between one and eight an error message will result and execution will terminate.

If L = 1 no regressions are possible and any regression output is omitted. The maximum degree of regression allowed

by RAGE, regardless of the value assigned to the argument D (degree of regression), is L-1. If D exceeds this value RAGE will set the degree of regression to L-1.

F. DEGREE OF REGRESSION...D

The degree of regression, D, is an integer value less than or equal to three. The degree of regression refers to the number of bias coefficients, β_1 , β_2 , $\ldots \beta_d$, that will be used in computing the unbiased estimate out to D terms.

In addition to the restrictions on D mentioned earlier, D will also be reduced for the regression that determines the variance coefficients, α_1 , α_2 , $\ldots \alpha_{d+1}$, when the number of subsamples sizes with a variance is less than D+1.

G. REDUCED GRAPHICS...RG

The reduced graphics argument, RG, allows the user to reduce the range of the vertical scale of the graph by eliminating outliers and only printing the number of outliers that exist. The vertical scale is reduced to the upper quartile plus 1.5 times the interquartile distance value and the lower quartile minus 1.5 times the interquartile distance value of the estimates from the smallest subsample size, NE(1). The vertical scale then becomes these values and the outliers are merely counted and printed on the graph at the ends of each box plot's upper (lower) quartile + (-) 1.5 times interquartile distance position. If there are no outliers for the NE(1) estimates, either or both extremes, the

vertical scale is further reduced to the first estimate value within these limits. RG = 1 will cause reduced graphics to be produced and RG = 0 will cause full scale graphics.

H. SCALING ESTIMATORS INDIVIDUALLY...SEI

The argument SEI allows the user to scale each estimator's vertical scale for the graphics separately or to the same scale. SEI = 0 causes all estimators' vertical scale to have the same range of values. The range of the vertical scale and whether outliers are printed or counted will depend on the graphics desired (RG = 0 or 1). Figures 4a, 4b and 4c are the results of three estimators scaled to the same scale (SEI = 0) with full scale graphics (RG = 0). Figures 5a, 5b and 5c are the results of three estimators scaled to the same scale (SEI = 0) but with reduced graphics (RG = 1).

If SEI = 1 each estimator's vertical scale will be scaled individually. The range of the vertical scale and whether outliers are printed or counted will depend on the graphics desired (RG = 0 or 1).

I. SETTING THE VERTICAL SCALE...SVS

To set the vertical scale an integer value of 1 is assigned to the argument SVS. SVS = 1 will cause the SEI argument to be ignored and the vertical scale of all the estimators' graphics will be set to those values assigned to YMIN and YMAX. When the argument SVS is in effect (SVS = 1) the argument RG is also in effect as far as whether outliers

are printed or counted (RG = 0 or 1) but the determination of the vertical scale by RG is overridden by SVS and is set to YMIN and YMAX. SVS = 0 causes RAGE to ignore values assigned to YMIN and YMAX and scaling is determined by the values assigned to the arguments RG and SEI. Figure 4d is an example of SVS = 1 and RG = 0 with the vertical scale set to that of Figures 4a, 4b, and 4c (YMIN=-1.2812, YMAX=13.9984). Figure 5d is an example of SVS = 1 and RG = 1 with the vertical scale set to that of Figures 5a, 5b and 5c (YMIN=1.0394, YMAX=9.1423).

J. MINIMUM VALUE OF THE VERTICAL SCALE...YMIN

The value YMIN is a real number assigned by the user as the lower limit of the vertical scale. If YMIN is assigned a value that is so large that it falls within the range of values that determine the body of any box plot then an error will occur and an abnormal ending will result.

K. MAXIMUM VALUE OF THE VERTICAL SCALE...YMAX

The value YMAX is a real number assigned by the user as the upper limit of the vertical scale. If YMAX is assigned a value that is so small that it falls within the range of values that determine the body of any box plot then an error will occur and an abnormal ending will result.

L. NUMBER OF ESTIMATORS...NEST

The argument NEST is an integer, 1, 2 or 3, which indicates the number of estimators that will be used to estimate the

parameter. An error message will be issued if NEST is not one of these values and execution will terminate.

M. ESTIMATOR FUNCTIONS...EST1, EST2, EST3

These arguments are the function names assigned to each of the estimators that are to be used in estimating the parameter. Each function must be written with a two argument calling sequence (i.e. call EST1(X,N)) where the first argument, X, must be the data array and the second argument, N, must be the number of data elements.

If there are less than three estimators then dummy arguments must be inserted in the calling sequence where subsequent estimators would normally appear (Suggestion...use a function of a previous estimator, i.e. EST1, as the dummy. RAGE will not provide duplicate output for these repeated functions unless NEST is increased to include them.). Each function must then be declared external in the main program. For an illustration of how the functions are written and declared see the example in Chapter IV.

N. DESCRIPTION OF ESTIMATORS...TTL1,TTL2,TTL3

The titles associated with each estimator can be passed as an argument through the call program (RAGE) provided there is a minimum of 120 characters between apostrophes (i.e. call RAGE(..., EST1,'---120 characters----',EST2,...)). An alternate and possibly easier method is to declare each title (TTL1, TTL2, TTL3) as a Real*8(15) array and assign

the characters that describe each estimator as data to each title. For an example of this method see the example in Chapter IV.

The user should note that the title associated with each estimator must immediately follow the estimator argument. As in the case of estimators, dummy titles must be inserted when the number of estimators requiring titles is less than three. Finally, it should be noted that the program will not execute properly unless titles of the correct format are included.

IV. EXAMPLE OF A PROGRAM USING RAGE

In the following example suppose a user has a set of iid data from which he wishes to estimate the population mean by using two estimators, the sample mean and the sample median. Assume that these estimators are given the abbreviated function names MN and MED and that the associated titles for each estimator are "The sample mean as an estimator of the population mean" and "The sample median as an estimator of the population mean." If the subsample sizes at which it is desired to examine the properties of these estimators are 33, 50, 71, 125, 166, 200, 250 and 500 the FORTRAN program may look as formatted on the following page.

REAL*4 X(50000), YMIN, YMAX

REAL*8 T1(15),T2(15)

INTEGER NEST,D,RG,SEI,SVS,M,N,L,NE(8)

DATA NE/ 33,50,71,125,166,200,250 500/

- C INSERT 8 CHARACTERS BETWEEN EACH SET OF APOSTROPHES UNTIL
- C TITLE IS COMPLETED AND FILL REMAINDER WITH BLANKS.

DATA T1/'THE SAMP', 'LE MEAN ', 'AS AN ES', 'TIMATOR ',

+'OF THE P','OPULATIO','N MEAN',8*' '/

DATA T2/'THE SAMP', 'LE MEDIA', 'N AS AN ', 'ESTIMATO',

+'R OF THE', 'POPULATI', 'ON MEAN', 8*' '/

EXTERNAL MN, MED

CALL RAGE(X,N,M,NE,L,D,RG,SEI,SVS,YMIN,YMAX,

+NEST,MN,T1.MED,T2,MN,T1)

STOP

END

REAL FUNCTION MN(X,N)

REAL X(N)

C AVERAGE OF N VALUES IN X

MN=0.0

DO 10 I=1,N

MN = MN + X(I)

10 CONTINUE

MN = MN/FLOAT(N)

RETURN

END

REAL FUNCTION MED(X,N)

REAL X(N)

- C MEDIAN OF N VALUES IN X
- C "PCTILE" IS A FUNCTION THAT RETURNS THE 50 PERCENTILE
- C NUMBER FROM THE DATA ARRAY X OF SIZE N.

MED = PCTILE(X,N,.5)

RETURN

END

In this example since only two estimators were used a dummy estimator and title had to be inserted as the arguments for the third case. Here the first estimator and its title were simply repeated.

V. A COMPARATIVE STUDY OF ESTIMATORS FOR THE GAMMA SHAPE PARAMETER

To demonstrate the use of the Regression Adjusted Graphics and Estimating (RAGE) package, two arrays of gamma distributed random variables with shape K=5.0 and K=0.2 were generated using the Naval Postgraduate School's random number generator--LLRANDOMII [Ref. 3]. Because these random numbers are independent and were drawn from the same distribution, they can be sectioned into independent and identically distributed blocks of size N. RAGE was specifically designed to evaluate estimators of parameters from just such iid populations. These two samples then should demonstrate the capabilities of the RAGE package to evaluate the bias, variance and distribution of estimators of a specified parameter from the populations.

In the following examples it is the shape parameter, K, of the gamma distribution that is being estimated. There are two primary estimators used in these examples. The first is the moment estimator (reciprocal of the estimated coefficient of variation squared), $K = \frac{1}{(C(X))^2} = \frac{X^2}{VAR(X)}$. The second

estimator is the maximum likelihood estimate (MLE) [Refs. 2,4] which is determined by a bisection search for the shape parameter, K, until the following equation is satisfied:

$$Ln(k) - Digamma(K) = Ln \overline{X} - \frac{\sum_{i=1}^{n} Ln X_{i}}{n}$$
 i=1, ..., n.

The X_i , i=1, 2, ..., n are the random numbers from a specified block of size n. The other two estimators investigated are jacknifed versions of the initial estimators. The jacknife routine [Ref. 5] with each of these estimators is a four fold jacknife which has the form

$$\tilde{\Theta}_{\star} = \frac{1}{4} \sum_{j=1}^{4} \tilde{\Theta}_{\star j}$$

where $\tilde{\theta}_{\star j} = 4(\tilde{\theta}_{all}) - 3(\tilde{\theta}_{j})$, $\tilde{\theta}_{all}$ is the estimate from the entire sample (n) and $\tilde{\theta}_{j}$ is the estimate with the j_{th} group missing. Each group is a set of one fourth of the data points.

Each of the four estimators is examined for varying subsample sizes and replications to determine how accurately each estimator estimates the shape parameter of the gamma distribution as the subsample size increases. The shape parameter of the gamma distribution was chosen as an example because the behavior of the many estimators which have been proposed for K is fairly well known. Roughly speaking, it is known that the moment estimator is quite efficient for K>2 but quite inefficient for K<1 even for large sample sizes. Bias and normality of these estimators is not documented. Again the jacknife is known to work well with moment estimators

even in small samples but no such results are known for the jacknifed MLE estimator except that it is asymptotically efficient.

For this investigation there are basically three examples representing different simulation scenarios for evaluating each of two cases, K=5.0 and K=0.2. They are:

- (a) Small subsample sizes (33 to 500), small
 replications (M=2);
- (b) Small subsample sizes (33 to 500), large
 replications (M=100);
- (c) Large subsample sizes (100 to 2000), large replications (M=25).

The first can be looked on as a pilot study to determine regions of interest for the two longer scale studies. However, the procedures are not fully sequential, unlike the usage of the RAGE methodology proposed by Heidelberger and Lewis [Ref. 1] for regenerative simulations.

With many of these examples another set of reduced graphics is included which reduces the vertical scale and provides graphics which are more suitable for examining the bias structure of the estimators. The reduced graphics truncates the outliers in the box plots giving only their number and not their position.

- A. EXAMINING THE GAMMA DISTRIBUTION FOR THE SHAPE PARAMETER (K=5.0)
 - 1. Case 1, Example 1: Small Subsample Sizes and Small Replications (K=5.0)

Figures 3a, 3b, 3c and 3d show the graphical and statistical results from estimating the shape parameter with the four different estimators. These graphs all have the same vertical scale so that meaningful comparisons can be made of the box plots and of the bias of each estimator.

One of the characteristics of the MLE estimator is that its estimates will asymptotically have the smallest variance of all estimators. For small subsample sizes (such as the case of Figures 3a & 3b) the asymptotically smaller variance of the MLE estimator is not apparent in the box plots. The body of the box plot for the MLE estimator for $n_1 = 33$ is smaller than the same box plot for the moment estimator. However, the MLE has more and larger outliers, indicating that the MLE is more nonnormal at this sample size than the moment estimator. If, however, the estimated standard deviation of the various subsample sizes are compared for each of the two primary estimators (Table 1) it can be seen that the MLE estimator consistently produces a smaller variance than does the moment estimator. From Figures 3a & 3b the bias in the two estimators appears comparable, starting high but becoming negligible by subsample size 250.

Table 1: Standard deviations of estimates of the shape parameter using the moment and MLE estimators for small sample sizes (replications = 2)

Standard Deviation

SAMPLE SIZE	MOMENT ESTIMATOR	MLE ESTIMATOR
33	1.517	1.306
50	.9942	.7151
71	.8829	.6051
100	.6312	.4612
125	.7725	.4823
166	.8310	.5114
250	.4660	.2772
500	.5589	.3087

Jacknifing is a technique that can be used on iid samples to reduce the bias in the estimates caused by the estimator [Ref. 5]. An estimator with a complete jacknife is asymptotically normal with the same variance as the unjacknifed estimator, but small sample properties are difficult to obtain analytically. Figures 3c & 3d are the jacknifed estimators and again because of the small number of estimates it is not apparent that the jacknife is contributing to nonnormality or increasing variance when the box plots are compared with those of Figures 3a & 3b. The increased normality, however, can be seen in the jacknifed moment estimator by comparing box plots (Figures 3a & 3c) and the coefficients of skewness (Table 2) with the nonjacknifed form. The change in normality or symmetry of the estimates from the jacknifed MLE estimator

is not discernable in a comparison of the box plots (Figures 3b & 3d) or the coefficients of skewness (Table 3).

Table 2: Skewness coefficients of the estimates of the shape parameter using the moment and jacknifed moment estimators (replications = 2)

			Skewness (Coefficients	
SAMPLE	SIZE	MOMENT	ESTIMATOR	JACKNIFED	FORM
33			.553	.327	
5 0			.076	348	
71			.339	.253	
100			.499	.157	
125		1	1.573	.724	
166		1	1.018	.501	
250		-	150	235	
500			N/A	N/A	

Table 3: Skewness coefficients of the estimates of the shape parameter using the MLE and jacknifed MLE estimators (replications = 2)

			Skewness	Coefficients	
SAMPLE	SIZE	MLE	ESTIMATOR	JACKNIFED	FORM
33			1.198	.050	
50			.510	.616	
71			.193	163	
100			.773	. 643	
125			1.451	1.216	
166			1.101	1.229	
250			030	.081	
500			N/A	N/A	

The bias in each estimator is depicted by the space between the dotted line and dashed line of each of the graphs. When the unbiased estimate (dotted line) approaches the estimated expected value (dashed line) then the bias becomes insignificant. Each estimator can be expected to vary in the amount of bias it has in its estimates and this bias can be expected to diminish as sample size increases. Comparing Figures 3a & 3b it appears that the MLE estimator has about the same bias as the moment estimator but this is hard to determine at this point since the bias coefficients were determined from a small number of estimates. In the estimates from the jacknifed estimators one would expect the bias to be reduced because jacknifing is specifically designed to remove the β_1 (1/n) term in the bias of the estimates but this is not obvious from the graphical comparisons (Figures 3a & 3c and Figures 3b & 3d). For the case of the MLE estimator the coefficient of the 1/n term, β_1 , has actually increased from 32.65 to 75.33 after jacknifing. The standard deviation of these bias terms are so large (19.14 and 16.23 respectively), though, that they suggest more estimates (increased replications) are necessary to better determine the bias.

Determining how much more bias one estimator has than another can also be accomplished by comparing the bias regression coefficients β_1 , β_2 , etc. The larger these coefficients are the greater is the bias of that particular


estimator. Comparing the coefficients for the moment and MLE estimators of Figures 3a & 3b show that the MLE estimator has a larger bias. For a subsample size of 500 and a three degree regression the bias for the moment estimator is

$$\frac{7.40128}{500} + \frac{183.099}{500^2} + \frac{1947.86}{500^3} = .0155$$

and the bias for the MLE estimator is

$$\frac{32.6486}{500} - \frac{1998.68}{500^2} + \frac{47308.0}{500^3} = .0577$$

These comparisons seem to indicate that the MLE estimator has more bias. This is not necessarily true, though, for reasons mentioned earlier. Increasing the number of replications will alleviate much of this uncertainty since more precision in the estimates of the bias coefficients will result.



RECIPROCAL OF SQUARED. CDEFFICIENT OF VARIATIONS OF THE SHAPE PARAN.
Figure 3a





Figure 3b



ESTIMATOR: FOUR FOLD JACKNIFED MOMENT ESTIMATOR OF THE SHAPE PARAMETER OF THE GAMMA DISTRIBUTION.

Figure 3c

45




Figure 3d

46

2. Case 1, Example 2: Small Subsample Sizes and Large Replications (K=5.0)

It was pointed out in Example 1 of this case that the small number of replications left some doubt as to the accuracy of the estimates of the bias coefficients as well as the normality of the estimates. Figures 4a to 4d (corresponding to Figures 3a through 3d) are for increased replications (M=100). This has the effect of increasing the population of estimates for each subsample size (n_k , k=1, ..., K) and the number of estimates of the bias coefficients $(\beta_1, \beta_2, \ldots)$ but holds the subsample size at which the estimators are examined small as before. On first observing the graphs, it becomes apparent from the box plots of the two smallest subsample sizes $(n_1=33 \text{ and } n_2=50)$ that the estimates are nonnormally distributed (Figures 4a & 4b). The jacknifed estimators remove some of this nonnormality (Figures 4c & 4c), especially for the jacknifed moment estimator. In effect, outliers appear now at both high and low values but considerable skewness still remains.

Here it is apparent by the statistical output that the MLE estimator has significantly less variance in its population of estimates than does the moment estimator (Table 4).

Table 4: Standard deviations of the estimates of the shape parameter using the moment and MLE estimators for varying sample sizes (replications = 100)

Standard Deviation

SAMPLE	SIZE	MOMENT ESTIMATOR	R MLE ESTIMATOR
33		1.486	1.396
50		1.175	1.075
71		.9818	.8549
100		.8008	.6636
125		.7242	.5918
166		.6499	.5145
250		.5082	.4036
500		.3417	.2730

The increased symmetry and normality by the jacknifed moment estimator is graphically visible if Figures 4a & 4c are compared. The change in symmetry or normality of the estimates of the jacknifed MLE estimator was not discernable in the graphics (Figures 3b & 3d) or skewness coefficients (Table 3) for Example 1. However, for increased replications, (M=100) if the box plots of Figures 4b & 4d are compared it appears that the population of MLE estimates are more normally distributed (outliers at both ends) after jacknifing. The movement toward symmetry is more obvious by comparing the skewness coefficients of the MLE estimates and the jacknifed MLE estimates.

The variance reduction, or lack of it, for each estimator when it is jacknifed can be determined by comparing the computed variances that result from a given subsample size and the variance coefficients, α_1 , α_2 , etc. If, for example, the variance coefficients (α_1 , α_2 , α_3 , and α_4) for each of the estimators (Figures 4a through 4d) are used to determine the variance for a subsample size of 500, the variances for each estimator would be:

VAR (MOMENT) =
$$\frac{58.37}{500} + \frac{174.72}{500^{1.5}} - \frac{1500.13}{500^2} + \frac{5446.25}{500^{2.5}} = .1273$$

VAR (MLE) = $\frac{67.52}{500} - \frac{961.91}{500^{1.5}} + \frac{10183.5}{500^2} - \frac{27503.3}{500^{2.5}} = .0848$
VAR (JNK MNT) = $\frac{79.20}{500} - \frac{457.44}{500^{1.5}} + \frac{5216.8}{500^2} - \frac{14533.1}{500^{2.5}} = .1357$
VAR (JNK MLE) = $\frac{62.66}{500} - \frac{825.2}{500^{1.5}} + \frac{8879.79}{500^2} - \frac{24484.2}{500^{2.5}} = .0827$

These computations show a lack of change in the variance when the estimators are jacknifed and agree with the statistical and graphical conclusions drawn earlier.

The bias in the MLE and moment estimators is difficult to compare graphically (Figures 4a & 4b) since the unbiased estimate approaches the estimated expected value so quickly and because of the compacting caused by the range of the vertical scale. For this reason reduced graphics are produced (Figures 5a through 5d), which the reader will recall

suppresses the outliers. Since the scale is reduced from a range of 15.28 (14.00 - (-1.28)) to 8.10 (9.14 - 1.04) or almost 50%, the evolution of the bias as subsample size increases becomes clearer, as Figures 5a & 5b demonstrate in comparison to Figures 4a & 4b. These graphs indicate that, for at least small subsample sizes, the moment estimator is a more biased estimator than the MLE estimator.

Reduced graphics are not of much use for the jacknifed estimators (Figures 5c & 5d) since the bias is almost completely removed by jacknifing. They are useful only in the sense that they are on the same scale as their nonjacknifed forms and a comparison of bias between estimators can only be done graphically if the graphics of estimators are on the same scale. This, however, was already accomplished from Figures 4a through 4d.


As was done for the variance, the amount of bias for a given subsample size can be estimated by dividing the coefficients, β_1 , β_2 , etc., by the sample size squared, cubed, etc., as appropriate and summing (See Chapter II "USAGE" for the mathematical formula). The computations will not be carried out here as in the case of the variance but it is useful to compare the β_1 coefficients of the estimators since these coefficients are likely to contribute the most significant amount of bias (they are divided by the smallest denominator). In the case of the moment estimator, β_1 is

16.50 and for the MLE estimator it is 14.77. This suspected greater bias by the moment estimator can be seen visually from the graphics. The smaller coefficients for β_1 of the jacknifed moment and MLE estimators are 1.47 and 4.09 respectively. This gives an indication of how much less the bias becomes when the estimators are jacknifed. This kind of comparison of β_1 coefficients should be done with caution, though, since subsequent coefficients (β_2 , β_3 , ...) may be so large that they contribute more to the bias than the β_1 coefficient. It should also be pointed out that these β_1 coefficients should be zero because, as mentioned earlier, the jacknife removes the β_1 (1/n) term. In fact, their estimated standard deviations are 4.00 and 5.67 respectively, so that they are within one standard deviation of zero.

As important as the size of these bias coefficients are their accuracy. Comparing the bias coefficients from Figures 5a through 5d in relation to their standard deviation with those of Figures 3a through 3d (Table 4) which were determined from only two replications, shows the advantage of large replication in estimating the bias of an estimator.

Table 5: Bias coefficients for each estimator's population of estimates and their standard deviations for small and large replications (M=2 and M=100)

	BIAS	NUMBER	OF REPLICATIONS
ESTIMATOR	COEFF.	TWO (2)	ONE HUNDRED (100)
	³ 1	7.40 (13.5)	16.49 (2.59)
MOMENT	⁸ 2	183.1 (1105.5)	-182.2 (204.1)
	³ 3	1947.9 (21284.5)	3659.04 (4526.5)
	3 ₁	32.65 (19.1)	14.77 (2.83)
MLE	³ 2	-1998.7 (1031.2)	-14.12 (220.2)
-	β 3	47308.0 (18073.1)	1602.74 (4798.3)
	⁸ 1	6.59 (11.0)	1.47 (4.01)
JNK MNT	^β 2	-912.54 (1016.4)	9.75 (335.5)
	^β 3	21772.7 (23318.6)	-1369.26 (7411.7)
	⁸ 1	75.33 (16.23)	4.09 (5.67)
JNK MLE	³ 2	-5815.6 (1450.6)	-203.3 (436.02)
	β ₃	112632.0 (32037.1)	793.11 (9243.2)








Figure 4b



ESTIMATORS FOUR FOLD JACKNIFED MOMENT ESTIMATOR OF THE SHAPE PARAMETER OF THE GAMMA DISTAIBULION.

Figure 4c

55



ESTIMATOR! FOUR FOLD JACKNIFED MAXIMUM LIKELIHOUD ESTIMATE OF THE SHAPE PARAMETER OF THE GAMMA DISTRIBULION. Figure 4d




Figure 5a (REDUCED GRAPHICS)




Figure 5b (REDUCED GRAPHICS)




Figure Sc (REDUCED GRAPHICS)




Figure 5d (REDUCED GRAPHICS)

Case 1, Example 3: Large Subsample Sizes and Large Replications (K=5.0)

Figures 4a through 4d showed the necessity of increasing subsample sizes in order to examine the normality of the estimates. Figures 6a through 6d are for increased subsample sizes (100 to 2000) with a large number of replications (M=25). The box plots in these figures show the increase in normality with increasing subsample size n_{ν} when they are compared with small subsample sizes (Figures 4a through 4d). The reduction in variability is also obvious by noticing the lack of outliers in the box plots and the smaller range of the vertical scale for larger sample sizes. The standard deviation for each of the estimators for small subsample sizes ($n_g=500$, Figures 4a through 4d) is compared to those for large subsample sizes $(n_6 = 2000, Figures 6a through 6d), Table 6. It can be seen$ that the variance is reduced for larger subsample sizes by the appropriate factor of two. However, the degrees of freedom in the standard deviation of the estimators are 25 at $n_6 = 2000$ and 100 at $n_8 = 500$. Again it is clear from these figures that jacknifing causes no lack of precision in either the MLE or moment estimators.

The bias in the moment and MLE estimators is difficult to compare from the graphics because of the range of the vertical scale. For this reason reduced graphics (Figures 7a & 7b) for these two estimators are produced. Reduced graphics for the jacknifed estimators would not be very useful since it


has been shown in previous examples that very little bias exists. For this reason they are omitted.


Table 6: Standard deviations of the population of estimates of the shape parameter for each estimator for subsample sizes 500 and 2000

	SAMPLE	SIZES
ESTIMATOR	n ₈ = 500	$n_6 = 2000$
MOMENT	.3417	.1592
MLE	.2730	.0910
JACKNIFED MOMENT	.3400	.1597
JACKNIFED MLE	.2759	.1090

A change seems to have occurred if a comparison is made of Figures 7a & 7b with those of Figures 5a & 5b. The graphics seem to indicate that the MLE's unbiased estimates have shifted from being biased on the high side to the low side for subsample size n_1 =100 and possibly n_2 =200. Also, it appears that the two estimators have about the same bias or that possibly the moment estimator has less bias. Looking further at the bias coefficients that determine these graphics, it can be seen that the coefficients in Figures 5a and 5b are estimated with more precision than those of Figures 7a and 7b. One may be tempted to assume that the MLE estimator is more biased for larger sample sizes. But this is not likely and the change in the bias structure for Figure 7b can be

attributed to the difference in the values of the bias coefficients (β_1 , β_2 , ...) compared to those of Figure 5b. These coefficients should be the same but the coefficients of Figure 5b were computed from 100 estimates (100 regressions) and those from Figure 7b only 25. The precision can be expected to be better in the first case. This is obviously the case if the standard deviation of the coefficients are compared, and more confidence can be placed in the bias structure of Figure 5b.







ESTIMATOR: MAXIMUM LIKELIHOOD ESTIMATE OF THE SHAPE PARAMETER OF THE GAMMA DISTRIBUTION.

Figure 6b

65



ESTIMATOR: FLUR FOLD JACKNIFED MOMENI ESTIMATOR OF THE SHAPE PARAMETER OF THE GAMMA DISTRIBUTION. Figure 6c






Figure 7a (REDUCED GRAPHICS)




Figure 7b (REDUCED GRAPHICS)

- B. EXAMINING THE GAMMA DISTRIBUTION FOR THE SHAPE PARAMETER (K=0.2)
 - 1. Case 2, Example 1: Small Subsample Sizes and Small Replications (K=0.2)

In the preceding case for K=5.0 four estimators of the shape parameter of the gamma distribution were evaluated for varying subsample sizes and replications. This evaluation is repeated here with the shape parameter changed from K=5.0 to K=0.2. This second set of comparisons is not only useful in demonstrating how the RAGE package shows the behavior of different estimators in regards to bias and variance, but also how these estimators may differ when the parameter being evaluated takes on different values.

Figures 8a through 8d are graphical results of the four estimators of the shape parameter, K=0.2. For these small subsample sizes and small population of estimates it is apparent from the graphics that the MLE estimator (Figure 8b) has tighter box plots than does the moment estimator (Figure 8a). This shows graphically that the variance for the MLE estimator is less than that of the moment estimator. This was not obvious when the shape parameter was 5.0. In Figures 3a & 3b of Case 1, Example 1, it was difficult to distinguish any difference in the box plots. This comparison shows how the MLE estimator is much better at reducing the variance when the actual shape parameter is as small as 0.2. Or, alternatively, it may be an indication of how much worse


the moment estimator is for estimating shape parameters that are small.


Figures 8c & 8d are the jacknifed forms of the estimators. It is not at all clear from the graphs that the jacknife is affecting the variance of the estimates. This lack of change could be attributed to the small number of estimates which suggest that the number of replications should be increased to achieve a better graphical evaluation.

In Case 1, Examples 1, 2 and 3, the coefficients of variance $(\alpha_1, \alpha_2, \alpha_3 \text{ and } \alpha_4)$ were helpful in determining which estimators produced the least variance. A look at α_1 in Figures 8b and 8d shows that they are negative numbers. Since α_1 often contributes the most significant amount to the variance, there is some suspicion that a determination of the variance by the use of these coefficients could result in negative variances for the MLE estimator and its jacknifed form. If α_2 and α_3 are not large positive numbers (relatively) it is especially likely. In these two cases α_2 is a relatively large positive number and negative variances do not occur if the calculations are carried through. However, for lesser degrees of regression (i.e. D=2) negative variances can occur. This is a result of the wide fluctuation of the variances of the small subsample sizes whose values are used as dependent variables in the regression which determine α_1 , α_2 , and α_3 . These variance coefficients are often


questionable when the variances of the population of estimates vary over a wide range and further suggest increasing the number of replications so that the variance coefficients can be more accurately determined.

The bias in the moment estimator (Figure 8a) appears to be considerably more than that of the MLE estimator (Figure 8b) when the graphs of figures are compared. This bias is further reduced when the jacknife is applied to the estimators (Figures 8c & 8d). A comparison of the bias is inadvisable at this point since the bias coefficients have large standard deviation values in comparison to their estimates. The β_1 coefficient, for example, of the MLE estimator is .0864 and its standard deviation is .189. As mentioned in previous examples, β_1 will normally contribute the most to the bias and since its standard deviation is larger than the estimate itself, its accuracy is highly questionable. Before any firm conclusions can be drawn concerning the bias of the estimators more estimates are required, which implies increasing the number of replications.






ESTIMATOR: MAXÍMUM LIKELÍHDOU ESTIMATE OF THE SHAPE PAKAMETER OF THE GAMMA DISTRIBUTION. Figure 8b



ESTIMATOR: FCUR FOLD JACKNIFED MOMENT ESTIMATUR OF THE SHAPE PARAMETER OF THE GAMMA DISTRIBUTION.

Figure 8c

75



ESTIMATOR: FCUR FULU JACKNIFED MAXIMUM LIKELIHOOD ESTIMATE OF THE SHAPE PARAMETER OF THE GAMMA DISTRIBUTION. Figure 8d

2. Case 2, Example 2: Small Subsample Sizes and Large Replications (K=0.2)

Figures 9a through 9d are for small subsample sizes but large replications (M=100). This increased number of estimates produces more definitive graphics for better evaluations of the bias and variance of the estimates produced by the estimators.

The graphs of the moment and MLE estimators (Figures 9a § 9b) show clearly as before that the MLE estimator has much less variance than does the moment estimator. Both, however, have positive skewness and high nonnormal estimates up to subsample size n_4 =125. The jacknifed form of the moment estimator has about the same variance as its nonjack-nifed form but is more symmetrically distributed. This can be seen in a comparison of the box plots of Figures 9a § 9c.

The distribution of the population of estimates for the jacknifed MLE estimator shows little if any difference graphically or statistically than the nonjacknifed estimates. This can be seen by comparing Figures 9b & 9d, which show little difference when the box plots are compared for various subsample sizes. For large values of the shape parameter, i.e. K=5.0, it could be seen from Figures 4b & 4d of Case 1, Example 1 that the jacknifed MLE estimator increased the symmetry of the estimates. This was obvious both in the graphics and by comparing the skewness coefficients. For K=0.2 the only indication that the estimates


are more symmetrically distributed is the comparison of the skewness coefficients for small subsample sizes $(n_1=33, n_2=50 \text{ and } n_3=71)$ of the MLE estimator and its jacknifed form (Figures 9b & 9d). The skewness appears to decrease slightly, but not discernably, for larger subsample sizes.

The amount of variance that was observed graphically can also be seen statistically by computing the variance of each estimator for designated subsample sizes using the variance coefficients α_1 , α_2 , α_3 and α_4 of each estimator. These coefficients for each estimator will result in positive variances. This is not always the case when the coefficients are determined from subsample sizes with a small population of estimates. This example illustrates the increased confidence that can be put into the variance coefficients as the number of estimates (replications) increases.


The bias again appears to be substantially greater for the moment estimator than the MLE estimator for comparable subsample sizes. Here, because of the range of the vertical scale, reduced graphics are produced for the moment and MLE estimators to better compare the bias of these estimators by reducing the scale (Figures 10a and 10b). A comparison of Figures 10a and 10b clearly shows the increased bias caused by the moment estimator. It was shown in Example 1 of Case 1 that the jacknifed estimators have little bias remaining in the estimates. This appears to be the case for

K=0.2, as indicated by the small bias coefficients of the jacknifed estimators (Figures 9c & 9d). For this reason, reduced graphics for the jacknifed estimators are omitted, since indications are they would show little more graphically than Figures 9c & 9d.


It is interesting to note that the bias of the moment estimator compared to that of the MLE estimator is not only greater, but greater for small values of the shape parameter (i.e. K=0.2) than for large values (i.e. K=5.0). This can be seen by comparing the bias in Figures 10a & 10b with that of Figures 5a & 5b. This indicates that the moment estimator is not only more biased than the MLE estimator but considerably more biased when the shape parameter being estimated is small.




ESTIMATOR: MOMENT ESTIMATOR (RECIPROCAL OF SQUARED COEFFICIENT OF VARIATION) OF THE SHAPE PARAMETER OF THE GAMMA DISTRIBUTION. Figure 9a




estimatory maximum likelihood estimate of the shape parameter of the gamm distribution. Figure $9\mathrm{b}$





ESTIMATORS FCUR FOLD JACKNIFED MAXIMUM LIKELIHDOD ESTIMATE OF THE SHAPE PARAMETER OF THE GAMMA DISTAIBULICM. Figure 9d



ESTIMATOR: MCMENT ESTIMATOR (RECIPROCAL OF SQUARED) COEFFICIENT OF VARIATION) OF THE SHAPE PARAMETER OF THE GAMMA DISTAIBUTION. Figure 10a (REDUCED GRAPHICS)




Figure 10b (REDUCED GRAPHICS) ESTIMATOR: MAXIMUM LIKELIHDOD ESTIMATE OF THE SHAPE PAKAMETER OF THE GAMMA DISTRIBUTION.

3. Case 2, Example 3: Large Subsample Sizes and Large Replications (K=0.2)

As a last example, graphs for large subsample sizes with a large number of replications (M=25) are produced for each estimator. The box plots of these graphs (Figures 11a through 11d) look similar to their counterparts for small sample sizes and large replications (Figures 9a through 9d). This is due to the difference in the vertical scale and does not indicate a lack of variance reduction by larger sample sizes. The range of the vertical scale of Figures 11a through 11d is .495 and is smaller than that of Figures 9a through 9d, which is .9865, by a factor or two. This is a simple but important illustration of the caution that must be exercised when comparing graphics that are not of the same scale.

Other than the reduced variance caused by larger sample sizes, the same conclusions that were reached in Example 2 of this case concerning the variance and the bias of the estimators is shown to hold here. The MLE estimator shows considerably less variance and bias than the moment estimator. The jacknifed moment estimator results in more normally distributed estimates and less bias. The jacknifed MLE estimator shows some improvement toward normality of its estimates and its variance has changed little.

As in Case 1 for K=5.0, the larger the subsample size the more normal are the population of estimates. This


increased normality can be seen graphically by comparing the graphs of Figures 11a through 11d with those of Figures 9a through 9d. The lack of outliers on the high side of the box plots for Figures 9a to 9d is an indication of convergence normality.


Table 7 summarizes the results of the comparisons of the four different estimators for K=5.0 and K=0.2. A comparison of the standard deviations shows the moment estimator to be consistently higher than the MLE estimator. These standard deviations, however, show little change when the primary estimators are jacknifed, indicating little or no change in variance by jacknifing. The bias values of the moment estimator are consistently higher and the root mean square error (r.m.s.e.) is considerably larger for K=0.2 in comparison to the MLE estimator, indicating how poor the moment estimator is for evaluating shape parameters of gamma distribution that have small values.

These conclusions were easily drawn from the graphs and the statistical output provided by the RAGE program and did not require extensive programming and analysis by the experimenter. This kind of expedient examination of estimators not only saves the experimenter time but reduces significantly the computer time required for analysis. This facilitation of analysis is the primary purpose of the RAGE methodology.

Table 7: Bias and variance comparisons for varying subsample sizes and shape parameters

SHAPE PRMTR	SAMPLE & SUBSAMPLE SIZE	M	ESTIMATOR	ESTIMATE	STD.DEV.	BIAS	R.M.S.E.
0.2	500	100	MOMENT	.2071	.002927	0071	.03012
			MLE	.2006	.0008701	006	.01057
			JN MOM	.2015	.003211	0015	.03215
			JN MLE	.2000	.008707	.00	.0087
0.2	2000	25	MOMENT	.2021	.003584	0021	.01804
			MLE	.2001	.0008417	.0001	.00421
			JN MOM	.2005	.003644	0005	.01823
			JN MLE	.1997	.0008966	.0003	.00494
5.0	500	100	MOMENT	5.012	.03417	012	.3419
			MLE	5.095	.02730	095	.2891
			JN MOM	4.981	.0340	.019	.3405
			JN MLE	5.057	.02759	057	.2817
5.0	2000	25	MOMENT	4.994	.03184	.006	.1593
			MLE	5.049	.01821	049	.1033
			JN MOM	4.988	.03194	.012	.16015
			JN MLE	5.014	.02180	-,014	.1099





ESTIMATOR: MAXIMUM LIKELIHOOD ESTIMATE OF THE SHAPE PAKAMETER OF THE GAMMA DISTRIBUTION. Figure 11b




Figure 11c

91




Figure 11d

92

RAGE PROGRAM LISTING

ERATE REGRESSION ADJUSTICATES OF AN INPUT RAICATIONS) OF N VALUES ONS CAN BE USED. THE OR SCALED INDIVIDUALLY	PARAMETERS * 4 ARRAY CONTAINING DATA XIMUM OF 50,000 DATA ELI	ER OF DATA ELEMENTS PER NNOT EXCEED 50,000 AND 1 ER OF SECTIONS (REPLICATION OF PYCEPT 100 AND MAN	ER ARRAY OF SIZE 8 CO ALUES OF NE MUST BE F. EMENT OF THE ARRAY NE NE (1) MUST NOT EXCEE	ER OF SUBSAMPLE SIZES FIION N. S ALSO THE NUMBER OF BO	EE OF REGRESSION FOR MELLINGE REDUCED BY RAGE INGH. D MUST be 1, 2 or 3	SCALING **** ALING IS ACCOMPLISHED BY ZE, NE (1) AND COMPUTING E RANGE OF THESE VALUES IS ASSUMED THAT ESTIMA
ISTED ESTIMATES AND BOX PLOTS WE DATA SERIES X CONTAING H EACH. UP TO 3 ESTIMATING GRAPHS CAN ALL BE OF THE SAM Y.	TA: LEMENTS CAN BE STORED IN X.	SECTION (N IS SAMPLE S MAN BUST NOT EXCRED 50, TIONS).	AINING SUBSAMPLE SIZE AN SHALLEST TO LARGEST AN BE GREATER THAN N. 12,500.	FROM NE(8) THAT WILL BE USED TO BOXPLOTS THAT WILL BE PRODUCED.	AN AND VARIANCE REGRESSIONS. F THE SAMPLE IS NOT LARGE	IY TAKING THE SMALLEST SUBSAMPLIG THE M* (N/NE(1)) ESTIMATES. IS THEN THE VERTICAL SCALE. (TES PROM NE(2), NE(3), ETC

RG

YMIN YMAX NEST

SVS

SEI

EST1 EST2 EST3

```
TITLES ASSOCIATED WITH EACH ESTIMATOR (EST1,2,3). A MAX OF 120 CHARACTERS CAN BE USED TO DESCRIBE EACH ESTIMATOR. EACH TITLE MUST BE DECLARED AS REALMS(15) ARRAYS UNLESS PASSED AS AN ARGUMENT OF THE CALEING PROGRAM RAGE. WHEN PASSING THE TITLE AS AN ARGUMENT THERE MUST BE A MINIMUM OF 120 CHARACTERS BETWEEN APOSTROPHES.
                                                                                                                                                                                                                                                                                                                                                                                                  SUBBOUTINE RAGE (X, N, M, NE, L, D, NG, SEL, SVS, YHIN, YMAX, NEST, EST1, TTL1, EST2, TTL2, EST3, TTL3)
REAL X (50000), ULH(4), Y (12500)
REAL*8 TTL1(15), TTL2(15), TTL3(15)
INTEGER NE(8), RG, SEL, SVS, SM
INTEGER D, L, NEST, TEST
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                9
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                    SH=NE(1)


LT=L-1

LT=L
        TTL1
TTL2
TTL3
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            30
```

C1

3

C



```
KEEP WIDEST PAIRCECT
                                                                                                                                                                                                                                                    KEEP HIDEST PAIR **
                                                                                                                                                                                                                                                                                                                                              VECTOR
                                                                                                                                                                                                                                                                                                                                              SCALE IN
                    SCALED
                                                                                                                                                                                                                                                                                                                                           FIND VERTICAL SCALE FOR 2ND ESTIMATOR.
IF (NEST : LT. 2) GO TO 50
CALL SECEST(XN H SH EST2 Y, KP)
IF (RG.EQ.1) CALL BELETO(Y, KP, YMAX, YMIN)
IF (RG.NE.1) CALL MAXMIN (Y, KP, YMAX, YMIN)
IF (YMIN : LT. ULH (2) | ULH (2) = YMIN
IF (YMAX : GT. ULH (4) | ULH (4) = YMAX
                                                                                                                                                                                                                                                 FIND VERTICAL SCALE FOR 3RD ESTIMATOR.

IF (NEST .LT. 3) GO TO 50

CALL SECEST (X N H SM EST 3 Y, KP)

IF (RG.EQ.1) CALL DELETO (Y, KP, YMAX, YMIN)

IF (RG.NE.1) CALL MAXHIN (Y, KP, YMAX, YMIN)

IF (YMIN .LT. ULH (2)) ULH (2) = YMIN

IF (YMAX .GT. ULH (4)) ULH (2) = YMAX
                    BE
                    Ţ
                    SI
                    GRAPH
TO 50
TO 75
ULH (4) = YMAX
ULH (4) = YMAX
DETERMINE HOW EACH G
IF (SVS : EQ: 1) GO T
IF (SRI : EQ: 1) GO T
                                                                                                                                                                                                                                                                                                                                                                  20
                                                                                                                                                                                                                                         υU
                                                                                                                                                                                                                                                                                                                           0000
                                                   00000
                                                                                                                                                        vv
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              υ
```

```
ORDER O
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          AND
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     AGRAPH EACH ESTINATOR SCALED TO ITS WIDEST POINTS, PIND VERTICAL SCALE FOR 1ST ESTINATOR AND GRAPH.

CALL SECEST(X N M NE(1), ESTINATOR AND GRAPH.

IF (RG.EO.1) CALL FOR 1ST ESTINATOR AND GRAPH.

IF (RG.EO.1) CALL BELTO (Y.KP.YMAX, YMIN)

ULH (2) = YMIN

ULH (4) = YMIN

ULH (4) = YMIN

WRITE (6, 101) ULH (2), ULH (4)

IF (N EST . LT. 2) GO TO 80
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                GRAPH
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                       AND GRAPH
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                         AND
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                  FIND VERTICAL SCALE FOR 2ND ESTIMATOR AND CALL SECEST (X N H NE 11) EST2 Y KP)

IF RG.EO. 1) CALL DELETO (Y, KP, YMAX, YMIN)

IF RG.NE. 1) CALL MAXMIN (Y, KP, YMAX, YMIN)

ULH (2) = YMIN

ULH (2) = YMIN

ULH (2) = YMIN

ULH (2) = YMIN

ULH (4) = YMAX

CALL PRST (X, N H, EST2 NE, L, RG, D, ULH, Y)

WRITE (6, 101) ULH (2), ULH (4)

IF (N EST , LT. 3) GO TO 80
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                         FIND VERTICAL SCALE FOR 3RD ESTINATOR AND IF (SVS.EQ.1) GO TO 78
CALL SECEST(X N N NE 1), EST3 Y KP)
IF (RG.EQ.1) CALL DELETO(Y, KP, YHAX, YHIN)
ULH (2) = YN IN
ULH (4) = YN X
ULH (4) = YN X
ULH (6) = YIN X
ULH (7) = YIN X
ULH (7) = YIN X
ULH (8) = YIN X
ULH (9) = YIN X
ULH (1) = YIN X
ULH (2) = YIN X
ULH (2) = YIN X
ULH (4) = YIN X
ULH (2) = YIN X
ULH (4) = YIN X
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              PETURE PORBUTAL PROBLEM PROBLEM PARTICITY PORBURANT TARREST PORBURANT TARREST PORBURANT TARREST PORBURANT TARREST PORBURANT TARREST PORBURANT TARREST PORBURANT TARREST PORBURANT TARREST PORBURANT TARREST PORBURANT TARREST PORBURANT TARREST PORBURANT TARREST PORBURANT TARREST PORBURANT TARREST PORBURANT TARREST PORBURANT TARREST PORBURANT TARREST PORBURANT TARREST PORBURANT TARREST PORBURANT TARREST PORBURANT TARREST PORBURANT TARREST PORBURANT TARREST PORBURANT TARREST PORBURANT TARREST PORBURANT TARREST PORBURANT TARREST PORBURANT TARREST PORBURANT TARREST PORBURANT TARREST PORBURANT TARREST PORBURANT TARREST PORBURANT TARREST PORBURANT TARREST PORBURANT TARREST PORBURANT TARREST PORBURANT TARREST PORBURANT TARREST PORBURANT TARREST PORBURANT TARREST PORBURANT TARREST PORBURANT TARREST PORBURANT TARREST PORBURANT TARREST PORBURANT TARREST PORBURANT TARREST PORBURANT TARREST PORBURANT TARREST PORBURANT TARREST PORBURANT TARREST PORBURANT TARREST PORBURANT TARREST PORBURANT TARREST PORBURANT TARREST PORBURANT TARREST PORBURANT TARREST PORBURANT TARREST PORBURANT TARREST PORBURANT TARREST PORBURANT TARREST PORBURANT TARREST PORBURANT TARREST PORBURANT TARREST PORBURANT TARREST PORBURANT TARREST PORBURANT TARREST PORBURANT TARREST PORBURANT TARREST PORBURANT TARREST PORBURANT TARREST PORBURANT TARREST PORBURANT TARREST PORBURANT TARREST PORBURANT TARREST PORBURANT TARREST PORBURANT TARREST PORBURANT TARREST PORBURANT TARREST PORBURANT TARREST PORBURANT TARREST PORBURANT TARREST PORBURANT TARREST PORBURANT TARREST PORBURANT TARREST PORBURANT TARREST PORBURANT TARREST PORBURANT TARREST PORBURANT TARREST PORBURANT TARREST PORBURANT TARREST PORBURANT TARREST PORBURANT TARREST PORBURANT TARREST PORBURANT TARREST PORBURANT TARREST PORBURANT TARREST PORBURANT TARREST PORBURANT TARREST PORBURANT TARREST PORBURANT TARREST PORBURANT TARREST PORBURANT TARREST PORBURANT TARREST PORBURANT TARREST PORBURANT TARREST PORBURANT TARREST PORBURANT TARREST PORBURANT TARREST PORBURANT TARREST PORBURANT TARREST PORBURANT TARREST PORBUR
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                           78
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                 00000000
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                       108
```

CO

C

00

```
DIMENSION NE(L)

INTEGER NEGERIA BIOLICE (B) D1 INIDIH UD DL LEDT, RG RNEK

INTEGER NEGERIA BIOLICE (B) D1 INIDIH UD DL LEDT, RG RNEK

REAL# (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (COUNTY (
                                    ELEMENT, SCALING'/
SCALE. !
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                           NO. OF REPLICATIONS (HUST BE <= 100)
NUMBER OF VALUES IN EACH REPLICATION (M*N MUST BE <= 50000)
USERS VECTOR WITH M CONSECUTIVE BATCHES OF N VALUES EACH
NO. OF SECTION SIZES (HUST BE BETWEEN 1 AND 8)
A RRAY WITH THE L SUBSAMPLE SIZES (HUST BE IN ASCENDING ORDER)
A BRRAY WITH THE L SUBSAMPLE SIZES (HUST BE IN ASCENDING ORDER)
A BEGREE OF THE REGRESSION (HUST BE <= 3 & <= L-1)
A MIN YMIN XMAX YMAX IN USER UNITS
ONLY ULH(2) AND ULH(4) NEED TO BE PASSED. OTHERS CALC. HERE
                                                                                                                                                                         SUBROUTINE PRST (X,N,M,EST,NE,L,RG,UD,ULH,Y)
REGRESSION ADJUSTED ESTIMATE
CALCULATES ESTIMATES FROM USER DATA USING "EST" FUNCTION
PLOTS BASIC OR RETRENCHED GRAPH ON LINE PRINTER
SMALLEST
RANGE OF
                                                                                                                                                                                                                                                                                                                                                           NAME OF USER WRITTEN ESTIMATING FUNCTION.
USAGE: FUNCTION NAME (X,N)
WHERE X IS A VECTOR WITH N'ENTRIES
   IF NE (1) IS NOT
TO FALL OUTSIDE
      INCREASING SIZE.
MAY CAUSE POINTS
                                                                                                                                                                                                                                                                                                                                                                       H
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                 ELACINES CONTRACT
                                                                                                                                                                                                                                                                                                                                                              EST
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                               988
                                                                                                                                                                                                                    0000000
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                      0000000000
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              C
```

```
FOR EACH OF M REPLICATIONS
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          -ULH (1) + (DLH (3) - DLH (1) / (ULH (3) - ULH (1))
LAST+6 LOCX (K) = LAST+6
CLEAR PLOT ARRAY

DO 3 J=1,50

DO 4 I=1,122

PLOT (I, 1) = BLK

CONTINUE

CONTINUE

SET HORIZONTAL XMIN, XMAX

ULH (3) = 1,2*ME(1)

SET SCALE

CALL SCALE

CALL SCALE

CALL SCALE

CALL SCALE

CALL SCALE

CALL SCALE

CALL SCALE

CALL SCALE

CALL SCALE

CALL SCALE

CALL SCALE

CALL SCALE

CALL SCALE

CONPUTE

LAST=-1

DO 5 K=1,L
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                 SIZE K
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                   DO 80 K=1 L

NBK=NB (K)

RMEK=NE (K)

SECTIONS COMPUTE ESTIMATORS FOR S.

CALL SECEST (X N.M. RNEK EST Y KP)

AVERAGE ESTIMATES OF SIZE NE (K) FOR KP=0

DO 10 I=1 M
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          DO 10 I=16

BH (K I) =6.

BB (K I) =6.

CONTINUE

CONTIN
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                  HB(K) = N/NE(K)
LOCI(K) = (NE(K)
IF(LOCI(K) - LT
LAST=LOCI(K)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                   15
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     180
                                                                                                                                                                                                                                                                                                                                                                                                    ပ
                                                                                                                                                                                                                                                                                                                                                                                                                                                                        U
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                      U
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                        ပ
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                    Ü
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                       ပ
```

```
\{(KP-2.) * KP + 3.\} / \{(KP-1.\} * (KP-2.) * (KP-3.\} \} / \{(KP*VAR*3.*(KP-1.) * (KP+KP-3.) / (KP*(KP-2.) * (KP-3.) \} / (VAR * VAR) - 3.
                                                                                                                                                                                                                                                                              AVERAGE REGRESSION COEPF. OVER M REPLICATIONS & CALC. VARIANCE
                                                                                                                                                                    IP D1. LT. 2 THEN NO REGRESSIONS OR PLOTING CAN BE DONE
            NSURE SAMPLE SIZE IS LARGE ENOUGH FOR T COMPUTATION.
                                                    (KP-2.)) # KP ( (KP-1.) # (KP-2.)) | GO TO 9
                                                                                                                                                                                 DO 94 I=1,D1
BA (I) = 0.
BY (II) = 0.
DO 95 J=1,H
BA (I) = BA (I) +B (I,J) ++2
CONTINUE
                                                                                                                                                                                                                                                       23
95
190
                                                                                                                                                      80
                                                                                                                                                                                                                 47
       COC
                                                                                                                                                              CCC
                                                                                                                                                                                                                                                                        ပပပ
```

```
I TH. X AXIS POSITION.

| / (DLH(3) - DLH(1)) + 1

ND THE REGRESSION CORFFICIENTS.
                                                                                                                                                                                                                                                                                                                                                       REGRESSION ON VARIANCES FROM EACH SEGMENT WITH A VARIANCE
                                                                                                                                                                                           SCALE ASYMPTOTE, BETAO, AND PLOT ACROSS PLOT.
J= (BA(1) - ULH(2) /* (DLH(4) - DLH(2) /* (ULH(4) - ULH(2) )
IF (J LT: 1:0R) /* (GT: 50) GO TO (17)
DO 120 I=3, INIDTH
IP (PLOT(I,3) - RQ. BLK) PLOT(I,3) = DASH
CONTINUE
                                                                   RSTABLISH REGRESSION LINE & ASYMPTOTE
0 T0 54"'
1-8*BA(I)**2)/(H*(H-1.))
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                               DO 98 I=3 IHIDTH
COMPUTE THE X VALUE FO
UX= (I-DLH(1)) + (ULH(3) -
COMPUTE THE Y VALUE FR
UX=BA(1)
DO 99 J=1,D
UX=UY+BA(J+1) / UX+MJ
CONTINUE
SCALE THE Y VALUE TO T
J= (UY-ULH(2)) + (DLH(4) -
IP (J - LT 1) OH J GT
IP (PLOT(I,J) · EQ. BLK)
                                                                                                                                                                                                                                                                                                                                                                                 K = H^* (M/NE(L))
LT = L
DT = D1
D0 = 111 \quad L = L
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                 B CONTINUE
CALL RREG
DO 77
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          CONT INUE
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     8 †
                                                                                                                                                                                                                                                                                                                                  120
                                                                                                                                                                                                                                                                                                                                                 SOO
                                                            ပပပ
                                                                                                     U
                                                                                                                                                                                                                                                             ပပ
                                                                                                                                                                                                υ
```

```
ENOUGH TO COMPUTE STATS.
 PLOT
               115
         85
                    130
                          ပပ
CCC
```

```
INT (10x 1221)

INT (10x 1221)

INT (10x 1221)

INT (10x 1221)

INT (10x 1221)

INT (10x 1221)

INT (10x 1221)

INT (10x 1221)

INT (10x 1221)

INT (10x 1221)

INT (10x 1221)

INT (10x 1221)

INT (10x 1221)

INT (10x 1221)

INT (10x 1221)

INT (10x 1221)

INT (10x 1221)

INT (10x 1221)

INT (10x 1221)

INT (10x 1221)

INT (10x 1221)

INT (10x 1221)

INT (10x 1221)

INT (10x 1221)

INT (10x 1221)

INT (10x 1221)

INT (10x 1221)

INT (10x 1221)

INT (10x 1221)

INT (10x 1221)

INT (10x 1221)

INT (10x 1221)

INT (10x 1221)

INT (10x 1221)

INT (10x 1221)

INT (10x 1221)

INT (10x 1221)

INT (10x 1221)

INT (10x 1221)

INT (10x 1221)

INT (10x 1221)

INT (10x 1221)

INT (10x 1221)

INT (10x 1221)

INT (10x 1221)

INT (10x 1221)

INT (10x 1221)

INT (10x 1221)

INT (10x 1221)

INT (10x 1221)

INT (10x 1221)

INT (10x 1221)

INT (10x 1221)

INT (10x 1221)

INT (10x 1221)

INT (10x 1221)

INT (10x 1221)

INT (10x 1221)

INT (10x 1221)

INT (10x 1221)

INT (10x 1221)

INT (10x 1221)

INT (10x 1221)

INT (10x 1221)

INT (10x 1221)

INT (10x 1221)

INT (10x 1221)

INT (10x 1221)

INT (10x 1221)

INT (10x 1221)

INT (10x 1221)

INT (10x 1221)

INT (10x 1221)

INT (10x 1221)

INT (10x 1221)

INT (10x 1221)

INT (10x 1221)

INT (10x 1221)

INT (10x 1221)

INT (10x 1221)

INT (10x 1221)

INT (10x 1221)

INT (10x 1221)

INT (10x 1221)

INT (10x 1221)

INT (10x 1221)

INT (10x 1221)

INT (10x 1221)

INT (10x 1221)

INT (10x 1221)

INT (10x 1221)

INT (10x 1221)

INT (10x 1221)

INT (10x 1221)

INT (10x 1221)

INT (10x 1221)

INT (10x 1221)

INT (10x 1221)

INT (10x 1221)

INT (10x 1221)

INT (10x 1221)

INT (10x 1221)

INT (10x 1221)

INT (10x 1221)

INT (10x 1221)

INT (10x 1221)

INT (10x 1221)

INT (10x 1221)

INT (10x 1221)

INT (10x 1221)

INT (10x 1221)

INT (10x 1221)

INT (10x 1221)

INT (10x 1221)

INT (10x 1221)

INT (10x 1221)

INT (10x 1221)

INT (10x 1221)

INT (10x 1221)

INT (10x 1221)

INT (10x 1221)

INT (10x 1221)

INT (10x 1221)

INT (10x 1221)

INT (10x 1221)

INT (10x 1221)

INT (10x 1221)

INT (10x 1221)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                        SUBROUTINE BOXPRT(Y, NY, IX, PLOT, RG)
PREPARES BOXPLOT FROM VECTOR Y (IN 2-D ARRAY
REAL Y (NY), ULH (4), DLH (4)
IMTEGER RG
CONTINUE
GO TO 14
BRITE(6,158) LABEL(4), (STAT(K,4),K=1,L1)
LT = L1
DO 33 I=1.15
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                      GO TO 444 (STAT (K,5), K=1,L1) (BA(I), I=1,D1)
                                                                                                                                                                                                                                                       12
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                             10 10 10
```

U

```
= DASH
= DASH
= DASH
= DASH
OUTLIERS ARE TO BE COUNTED AND THE NUMBER PRINTED.
GO TO 55
[122,50], DASH, CBAR, CROSS, CSTR, CO, NUM (10)
                           BAB/'|'/'CSTB/'*'/'CROSS/'+'/'CO/'0'/
TO 5
                                                   CINTS JUST SHOW THE POINTS
                                                                                              LS OUTSIDE HINDON
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                 LLS OUTSIDE HINDOW
                                                                                                                                                                                                                                                                  S
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                        20
```

```
UP WITH HI-CROSS POINTER (LAST POINT LE XHI)
INX=J
AMD: Y (I) . LE. CHI) PLOT (IX, J) = CO
PLOT (IX, J) = CSTR
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                  NEXT LINE ENDS UP WITH HI-CROSS POINTER (LAST POINT LE XHI) IP (Y (I) . LE. XHI) IHX=J IP (Y (I) . GT. XHI) . AND. Y (I) . LE. CHI) PLOT (IX, J) = CONTINUE
IF(Y(I).LT.CLOW) PLOT(IX,J)=CSTR
IF(Y(I).LT.CLOW) GO TO 30
IF(I).LT.CLOW, AND.Y(I).LT.XLOW) PLOT(IX,J)=CO
IF(I).LT.CLOW, AND.Y(I).LT.XLOW) PLOT(IX,J)=CO
IF(I).LT.CLOW, AND.Y(I).LT.XLOW) PLOT(IX,J)=CO
IF(X(I).LT.CLOW, AND.Y(I).LE.XLOW)
IEXT LINE ENDS UP WITH HI-CROSS POINTER (LAST POINT
IF(Y(I).LE.XHI) IHX=J
IF(Y(I).LE.XHI) IHX=J
IF(Y(I).LE.XHI) IHX=J
IF(Y(I).LE.XHI) PLOT(IX,J)=CSTR
                                                                                                                                                                                                                                                                               SCALE TO INTERQUARTILE + (-) INTERQUARTILE DISTANCE
                                                                                                                                                                                                                                                                                                                                                                                                                                                       PLOT (IX,J) =CO
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                      T NUMBER OF OUTLIERS UNLESS 0.
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                      (K=III
|= (CHI-YMIN) *VSCALE
|J=50
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                       FILL BARS ABOVE AND BELOW THE DO 32 I=ILX, IQ1 PLOT(IX, I)=CBAR
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                               LOW-YMIN) MVSCALE
                                                                                                                                                                                                                                                                                                                   55
                                                                                                                                                                                                                      30
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                  31
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                             96
                                                                                                                                                              25
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                             26
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                      22
```

ပပ

ပပ

```
A MAX SCALE (ULH DLH)
COMPUTES X SCALE (ULH DLH)
COMPUTES X SCALE (ULH DLH)
X MIN = ULH (1)
X MAX = ULH (1)
Y MAX = ULH (2)
Y MAX = ULH (3)
Y MAX = ULH (4)

                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                        SUBROUTINE RREG (X, Y, B, M, N, IX1, IX2)

ROBUST REGRESSION ON Y=XEB

X=M BY N MATRIX CONTAINED IN AN ARRAY OF

B=N-VECTOR CONTAINED IN AN ARRAY OF DIM

Y = WORK ARRAY OF DIM (IX1)

XX, XXI=WORK ARRAY OF DIM (IX1)

XY=WORK AR
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          E DE LINE CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONTROL CONT
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                           を存在をいり
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                66
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                           60
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            0000000000
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                             J
```

```
L=O
CALL VHULPH(X,Y,H,N,N,IX1,IX1,XY,IX2,IER)
CALL LINV2P(XX,M,M,X,Z,XXI,LHK,IER)
CALL LINV2P(XXI,XY,N,N,K,IX2,IX2,B,IX2,IER)
CALL VHULPP(XXI,XY,N,N,K,IX2,IX2,B,IX2,IER)
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
RETURN
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                 ZO
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          NUMPRT PLOTS THE NUMBER IK IN THE 2-D ARRAY PLOT CENTERED THE PLOT (IX, J) POSITION.

IX = COLUMN OF MATRIX PLOT WHERE NUMBER IS TO BE PRINTED.

J = ROW OF MATRIX WHERE MUMBER IS TO BE PRINTED.

IK = NUMBER TO BE PRINTED

PLOT = 2-D ARRAY WHERE NUMBER IS TO BE PLOTED.
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     | EGER*2 | NUM (10) | PLOT (12250) | EK. LT. 100 | GO TO | IK. LT. 1000 | GO TO | IK. LT. 1000 | GO TO | IK. LT. 10000 | IM. (11000+1) | IK. LT. 10000 | IM. (11000+1) | IK. LT. 10000 | IM. (11000+1) | IK. IK. IT. 10000 | IM. (1100+1) | IK. IT. 10000 | IM. (1100+1) | IK. IT. 10000 | IM. (1100+1) | IK. IT. 10000 | IM. (1100+1) | IK. IT. 10000 | IM. (1100+1) | IK. IT. 10000 | IM. (1100+1) | IK. IT. 10000 | IM. (1100+1) | IK. IT. 10000 | IM. (1100+1) | IK. IT. 10000 | IM. (1100+1) | IK. IT. 10000 | IM. (1100+1) | IK. IT. 10000 | IM. (1100+1) | IK. IT. 10000 | IM. (1100+1) | IK. IT. 10000 | IM. (1100+1) | IK. IT. 10000 | IM. (1100+1) | IM. (1100+1) | IK. IT. 10000 | IM. (1100+1) | IM. (1100+1) | IM. (1100+1) | IM. (1100+1) | IM. (1100+1) | IM. (1100+1) | IM. (1100+1) | IM. (1100+1) | IM. (1100+1) | IM. (1100+1) | IM. (1100+1) | IM. (1100+1) | IM. (1100+1) | IM. (1100+1) | IM. (1100+1) | IM. (1100+1) | IM. (1100+1) | IM. (1100+1) | IM. (1100+1) | IM. (1100+1) | IM. (1100+1) | IM. (1100+1) | IM. (1100+1) | IM. (1100+1) | IM. (1100+1) | IM. (1100+1) | IM. (1100+1) | IM. (1100+1) | IM. (1100+1) | IM. (1100+1) | IM. (1100+1) | IM. (1100+1) | IM. (1100+1) | IM. (1100+1) | IM. (1100+1) | IM. (1100+1) | IM. (1100+1) | IM. (1100+1) | IM. (1100+1) | IM. (1100+1) | IM. (1100+1) | IM. (1100+1) | IM. (1100+1) | IM. (1100+1) | IM. (1100+1) | IM. (1100+1) | IM. (1100+1) | IM. (1100+1) | IM. (1100+1) | IM. (1100+1) | IM. (1100+1) | IM. (1100+1) | IM. (1100+1) | IM. (1100+1) | IM. (1100+1) | IM. (1100+1) | IM. (1100+1) | IM. (1100+1) | IM. (1100+1) | IM. (1100+1) | IM. (1100+1) | IM. (1100+1) | IM. (1100+1) | IM. (1100+1) | IM. (1100+1) | IM. (1100+1) | IM. (1100+1) | IM. (1100+1) | IM. (1100+1) | IM. (1100+1) | IM. (1100+1) | IM. (1100+1) | IM. (1100+1) | IM. (1100+1) | IM. (1100+1) | IM. (1100+1) | IM. (1100+1) | IM. (1100+1) | IM. (1100+1) | IM. (1100+1) | IM. (110
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                             = NUM (I 10+1)

= NUM (I 1+1)

= NUM (I 1+1)
```

```
COMPUTE STIMATES "EST" KAP LENGTH NEK

COMPUTE ESTIMATES "EST" FOR SECTION LENGTH NEK

NEAL X (5000), Y (12500)

NEAL X (12500)

NEAL X (12500), Y (12500)

NEAL X (12500), Y (12500)

NEAL X (12500), Y (12500)

NEAL X (12500), Y (12500)

NEAL X (12500), NEK)

NEW CONTINUE

NEW C
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            SUBROUTINE MAXMIN(Y, N, YMAX, YMIN)

RETURNS HAX AND HIN VALUES OF VECTOR Y OF LENGTH N

YMAX=Y {1}

YMIN=Y {1}

YMAX=Y {1}

Y
                                                                                                                                                                                                                                                                                                                                                                                                                                                               FUNCTION PCTILE (YNE) OF N VALUES IN CALL PXSORT (Y, 1, N)
CALL PXSORT (Y, 1, N)
I = MAXO (INT (R), 1, N)
                                                                                                                                                                                          Jo = NUM (I 10+1)
10* 10)
= NUM (I 1+1)
= NUM (I1+1)
                                       PLOT (IX+1, J) = NUM (I1+1)

GO TO 22

I 10 = IK/10

PLOT (IX-1) = NUM (I10+1)

PLOT (IX-1) = NUM (I1+1)

GO TO 22

PLOT (IX, J) = NUM (IK+1)

RETURN
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                             U
```

```
ບບບ ບ
```

LIST OF REFERENCES

- 1, Heidelberger, P. and Lewis, P. A. W., "Regression-Adjusted Estimates for Regenerative Simulations, with Graphics," Communications of the ACM, v. 24, pp 260-273, April 1981.
- 2. Cox, D. R. and Lewis, P. A. W., The Statistical Analysis of Series of Events, Mehteun & Co. LTD, 1966.
- 3. Lewis, P. A. W. and Uribe, L., The New Naval Postgraduate School Random Number Package LLRANDOM, Naval Postgraduate School Rept. NPS55-81-005, Monterey, California, 1981.
- 4. Davis, Harold T., <u>Tables of the Higher Mathematical</u>
 <u>Functions</u>, 1st ed., v. 1, Principia Press, Inc., 1933.
- 5. Miller, R. G., Jr., "The Jacknife--a Review," Biometrika 61, April 1974.

INITIAL DISTRIBUTION LIST

		No.	Copie
1.	Defense Technical Information Center Cameron Station Alexandria, Virginia 22314		2
2.	Library, Code 0142 Naval Postgraduate School Monterey, California 93940		2
3.	Department Chairman, Code 55 Department of Operations Research Naval Postgraduate School Monterey, California 93940		1
4.	Captain David G. Linnebur, USMC Headquarters Marine Corps (MPI 20) Washington, D.C. 20380		1
5.	Professor P. A. W. Lewis, Code 55LW Naval Postgraduate School Monterey, California 93940		5
6.	Commandant of the Marine Corps, Code RDJS-40 Headquarters Marine Corps Washington, D.C. 20380		1
7.	Dean of Research, Code 012 Naval Postgraduate School Monterey, California 93940		1
8.	Professor P. A. Jacobs, Code 55JC Naval Postgraduate School Monterey, California 93940		1
9.	Dean of Information and Policy Sciences, Code Naval Postgraduate School Monterey, California 93940	01	1
10.	Professor D. P. Gaver, Code 55GV Naval Postgraduate School	•	1

11.	Lt. Col. J. F. Mullane, Code 0309 Naval Postgraduate School Monterey, California 93940	1
12.	Captain Nick A. Sottler Marine Corps Recruiting Station 4727 Wilshire Blvd.	1
	Los Angeles, California 90010	
13.	Captain H. Keith Sullivan Officer Candidate School MCDEC Quantico, Virginia 22134	1